

インバータ FREQROL-F シリーズ

電圧	形式	適用モータ		外径寸法(mm)			旧形式 シリーズ	旧形式 シリーズ
		出力容量 (KW)	出力容量 (KVA)	W	H	D		
三相 200 V	FR-F820-0.75K	0.75	1.9	110	260	110	FR-F720-0.75K	FR-F520-0.75K
	FR-F820-1.5K	1.5	3	110	260	125	FR-F720-1.5K	FR-F520-1.5K
	FR-F820-2.2K	2.2	4.2	150	260	140	FR-F720-2.2K	FR-F520-2.2K
	FR-F820-3.7K	3.7	6.7				FR-F720-3.7K	FR-F520-3.7K
	FR-F820-5.5K	5.5	9.1				FR-F720-5.5K	FR-F520-5.5K
	FR-F820-7.5K	7.5	13	220	260	170	FR-F720-7.5K	FR-F520-7.5K
	FR-F820-11K	11	18				FR-F720-11K	FR-F520-11K
	FR-F820-15K	15	23	220	300	190	FR-F720-15K	FR-F520-15K
	FR-F820-18.5K	18.5	29	250	400	190	FR-F720-18.5K	FR-F520-18.5K
	FR-F820-22K	22	34				FR-F720-22K	FR-F520-22K
	FR-F820-30K	30	44				FR-F720-30K	FR-F520-30K
	FR-F820-37K	37	55	325	550	195	FR-F720-37K	FR-F520-37K
	FR-F820-45K	45	67	425	550	250	FR-F720-45K	FR-F520-45K
	FR-F820-55K	55	82	435	550	250	FR-F720-55K	FR-F520-55K
三相 400 V	FR-F840-0.75K	0.75	1.9	150	260	140	FR-F740-0.75K	FR-F540-0.75K
	FR-F840-1.5K	1.5	3				FR-F740-1.5K	FR-F540-1.5K
	FR-F840-2.2K	2.2	4.6				FR-F740-2.2K	FR-F540-2.2K
	FR-F840-3.7K	3.7	6.9				FR-F740-3.7K	FR-F540-3.7K
	FR-F840-5.5K	5.5	9.1				FR-F740-5.5K	FR-F540-5.5K
	FR-F840-7.5K	7.5	13	220	260	170	FR-F740-7.5K	FR-F540-7.5K
	FR-F840-11K	11	18				FR-F740-11K	FR-F540-11K
	FR-F840-15K	15	24	220	300	190	FR-F740-15K	FR-F540-15K
	FR-F840-18.5K	18.5	29				FR-F740-18.5K	FR-F540-18.5K
	FR-F840-22K	22	34				FR-F740-22K	FR-F540-22K
	FR-F840-30K	30	43	250	400	190	FR-F740-30K	FR-F540-30K
	FR-F840-37K	37	54	325	550	195	FR-F740-37K	FR-F540-37K
	FR-F840-45K	45	66	435	550	250	FR-F740-45K	FR-F540-45K
	FR-F840-55K	55	84				FR-F740-55K	FR-F540-55K