

インバータ FREQROL-E シリーズ

電源	形式	適用モータ	出力容量	外径寸法(mm)		
		(KW)	(KVA)	W	H	D
三相 200V	FR-E720-0.1K	0.1	0.3	68	128	80.5
	FR-E720-0.2K	0.2	0.6			
	FR-E720-0.4K	0.4	1.2	68	128	113
	FR-E720-0.75K	0.75	2.0	68	128	133
	FR-E720-1.5K	1.5	3.2	108	128	136
	FR-E720-2.2K	2.2	4.4			
	FR-E720-3.7K	3.7	7.0	170	128	143
	FR-E720-5.5K	5.5	9.5	180	260	165
	FR-E720-7.5K	7.5	12.1			
	FR-E720-11K	11	18.7	220	260	190
FR-E720-15K	15	23.9				
三相 400V	FR-E740-0.4K	0.4	1.2	140	150	114
	FR-E740-0.75K	0.75	2.0			
	FR-E740-1.5K	1.5	3.0	140	150	135
	FR-E740-2.2K	2.2	4.6			
	FR-E740-3.7K	3.7	7.2			
	FR-E740-5.5K	5.5	9.1	220	150	147
	FR-E740-7.5K	7.5	13.0			
	FR-E740-11K	11	17.5	220	260	190
FR-E740-15K	15	23.0				
単相 200V	FR-E720S-0.1K	0.1	0.3	68	128	80.5
	FR-E720S-0.2K	0.2	0.6			
	FR-E720S-0.4K	0.4	1.2	68	128	143
	FR-E720S-0.75K	0.75	2.0	108	128	136
	FR-E720S-1.5K	1.5	3.2	108	128	161
	FR-E720S-2.2K	2.2	4.4	140	150	156
単相 100V	FR-E710W-0.1K	0.1	0.3	68	128	80.5
	FR-E710W-0.2K	0.2	0.6	68	128	111
	FR-E710W-0.4K	0.4	1.2	68	128	143
	FR-E710W-0.75K	0.75	2.0	108	128	155