

インバータ      FREQROL-A シリーズ

電圧	形式	適用モータ (KW)	在庫	出力容量 (KVA)	外径寸法(mm)			旧形式	旧形式
					W	H	D	シリーズ	シリーズ
三相 200V	FR-A820-0.4K	0.4	◎	1.1	110	260	110	FR-A720-0.4K	FR-A520-0.4K
	FR-A820-0.75K	0.75	◎	1.9	110	260	125	FR-A720-0.75K	FR-A520-0.75K
	FR-A820-1.5K	1.5	◎	3	150	260	140	FR-A720-1.5K	FR-A520-1.5K
	FR-A820-2.2K	2.2	◎	4.2				FR-A720-2.2K	FR-A520-2.2K
	FR-A820-3.7K	3.7	◎	6.7	220	260	170	FR-A720-3.7K	FR-A520-3.7K
	FR-A820-5.5K	5.5	◎	9.1				FR-A720-5.5K	FR-A520-5.5K
	FR-A820-7.5K	7.5	◎	13	FR-A720-7.5K	FR-A520-7.5K			
	FR-A820-11K	11	◎	18	220	300	190	FR-A720-11K	FR-A520-11K
	FR-A820-15K	15	◎	23	250	400	190	FR-A720-15K	FR-A520-15K
	FR-A820-18.5K	18.5	◎	29				FR-A720-18.5K	FR-A520-18.5K
	FR-A820-22K	22	◎	34	325	550	195	FR-A720-22K	FR-A520-22K
	FR-A820-30K	30	◎	44				FR-A720-30K	FR-A520-30K
	FR-A820-37K	37	◎	55	435	550	250	FR-A720-37K	FR-A520-37K
	FR-A820-45K	45	◎	67				FR-A720-45K	FR-A520-45K
FR-A820-55K	55	◎	82	465	700	250	FR-A720-55K	FR-A520-55K	
三相 400V	FR-A840-0.4K	0.4	◎	1.1	150	260	140	FR-A740-0.4K	FR-A540-0.4K
	FR-A840-0.75K	0.75	◎	1.9				FR-A740-0.75K	FR-A540-0.75K
	FR-A840-1.5K	1.5	◎	3				FR-A740-1.5K	FR-A540-1.5K
	FR-A840-2.2K	2.2	◎	4.6				FR-A740-2.2K	FR-A540-2.2K
	FR-A840-3.7K	3.7	◎	6.9				FR-A740-3.7K	FR-A540-3.7K
	FR-A840-5.5K	5.5	◎	9.1	220	260	170	FR-A740-5.5K	FR-A540-5.5K
	FR-A840-7.5K	7.5	◎	13				FR-A740-7.5K	FR-A540-7.5K
	FR-A840-11K	11	◎	18	220	300	190	FR-A740-11K	FR-A540-11K
	FR-A840-15K	15	◎	24				FR-A740-15K	FR-A540-15K
	FR-A840-18.5K	18.5	◎	29	250	400	190	FR-A740-18.5K	FR-A540-18.5K
	FR-A840-22K	22	◎	34				FR-A740-22K	FR-A540-22K
	FR-A840-30K	30	◎	43	325	550	195	FR-A740-30K	FR-A540-30K
	FR-A840-37K	37	◎	54				FR-A740-37K	FR-A540-37K
	FR-A840-45K	45	◎	66	435	550	250	FR-A740-45K	FR-A540-45K
	FR-A840-55K	55	◎	84				FR-A740-55K	FR-A540-55K
	FR-A840-75K	75	◎	110					
	FR-A840-90K	90	◎	137					
FR-A840-110K	110	○	165						
FR-A840-132K	132	○	198						

